BAT WIRELESS

DATASHEET

IPEX Antenna Connector

Model No:

BWIPX-4-001E

Internal Model No：

BWIPX-4-001E

Description:

IPEX-4 Board-End Connector

Features：

0-6000MHz

IPEX-4 male

Size: 1.7mm x 1.7mm x 0.6mm

RoHS & REACH Complaint

BAT WIRELESS

CONTENTS

1.	Description	3
2.	Specifications	4
3.	Dimensions	5
3.1	Actual Picture	5
3.2	Parts Drawing	5
4.	Test Equipment	6-7

BAT WIRELESS

BWIPX-4-001E

Part Number Description

BW	Company	BAT WIRELESS
IPX	Name	IPEX connector
-	Constant	Constant
4	Generation	Fourth generation
-	Constant	Constant
001	Number	001
E	Type	Board-End connector

1. Description

Bat Wireless BWIPX-4-001E is an ultra-small RF coaxial connector with a frequency range of 0~6 GHz, suitable for mainstream wireless communication frequency bands, such as Wi-Fi,Connection of Bluetooth, GPS, 4G/5G antenna and other modules. Use a super-small design and small size suitable for high-density PCB layouts. The interface type is a male terminal, with a central pin terminal.Usually soldered on the PCB and used with the female head. Low loss design, optimized process and coaxial structure to ensure low interpolation loss for signal transmission.

Typical Applications:

Wireless module: Wi-Fi, Blue Tooth module, cellular module

Antenna connection: PCB antenna, external FPC,rubber antenna

Consumer electronics: notebooks, tablets, smart home devices

Bat Wireless provides customized services to optimize your device, we have a mature R&D team that can respond quickly to meet your needs. If you have any requirements, please contact our sales and FAE.

BAT WIRELESS

2. Specification

Parameters	Typ.	Unites	Notes
Electrical Characteristics			
Antenna Type	IPEX Antenna Connector		
Frequency Range	0-6000	MHz	
Input Impendence	50	Ω	
Contact resistance	-	mΩ	
Insulation resistance	500	MΩ	
Insert Loss	0.15	dB(6GHz)	
RF leakage	200	V	
Durability	500	Times	
PLUG / JACK	-	mm	
DC Voltage	-	V	
Mechanical Characteristics			
Dimensions	1 . 7 x 1 . 7 x 0 . 6	mm	
Connector Type	Jack		
Cable Type	-		
Cable Length	-	mm	
Mount way	SMD		
Color	Gold		
Meterial	Gold-Plated Brass		
Weight	0.038	g	
Environmental Characteristics			
Waterproof Rating	-		
ROHS Complaint	Yes		
Operating Temperature	-45~ +85	℃	
Storage Temperature	-45~ +85	℃	

BAT WIRELESS

3 . Demensions

3.1 Actual Picture

3.2 Parts Drawing



BAT WIRELESS

4 . Test Equipment

Keysight/E5071C Network Analyzer

R&S/CMW500 Comprehensive tester

R&S/SMBV100B Signal Source



DT-3500 Datasheet / System Specifications	
Specification:	**Description**
Test Frequency :	400MHz-8.5GHz
System Size :	L*W*H=4*3.5*3.5m
Number of Probes :	23 (Probe) + 1 (link)
Interval Angle :	15º
Sampling Diameter :	2200mm
Carring Capacity :	≦40kg

Testing Capability	Description
Active measurement	**Capability :** TRP、TIS、EIRP、EIS,. etc **Mode :** 2G/3G/4G/5G、Wi-Fi b/g/n/a/ac/ax、BT、NB-IOT、Cat-M (eMTC)、GPS/BEIDOU/GLONASS、ZigBee、LoRa(Non-Signaling),.etc
Pasive measurement	**Test category :** Gain、Efficiency、2D pattern、3D pattern、Pattern roundness、Axial Ratio, ECC,Phase center,. etc **Polarization :** Circular polarization, linear polarization, elliptical polarization



RF Link diaram of multi probe spherical near-field testing system

RF Link Overview



RF Link of Passivemeasurement



RF Link Overview



RF Link of Passivemeasurement



DECLARATION:

Legal Notice: In order to provide users with better service, Shenzhen Bat Wireless Technology Co., Ltd. (hereinafter referred to as ‘ Bat Wireless ’) will endeavour to present users with detailed and accurate product information in this manual. However, due to the time-sensitive nature of the content in this manual, Bat Wireless cannot guarantee the timeliness and applicability of this document at all times. Bat Wireless reserves the right to update the content of this manual without prior notice. To obtain the latest information, we kindly request users to regularly visit the Bat Wireless official website or contact Bat Wireless staff. Thank you for your understanding and support!

Copyright Notice: All content in this product manual (including text, charts, logos, and designs) is protected by copyright law and international copyright treaties. No entity or individual may reproduce, modify, distribute, or use any part or all of this manual in any form (including electronic, mechanical, photocopying, etc.) without prior written authorisation from our company. Infringers will be held legally liable. All rights reserved.

Trademark Notice: All product names and corporate logos of Bat Wireless mentioned in this manual are the lawful property of our company (including affiliated companies). Unauthorised use, reproduction, or imitation is strictly prohibited. Third-party trademarks referenced in this manual are the property of their respective owners, and their use is solely for illustrative purposes and does not imply any commercial affiliation or authorisation. Our company reserves all rights to pursue legal action against any infringement.

Disclaimer: The product information contained in this manual is for reference only. Actual product performance may vary depending on the usage environment and configuration differences. Our company makes no express or implied warranties regarding the accuracy, completeness, or applicability of the content of this manual and shall not be liable for any direct or indirect losses arising from the use or inability to use the content of this manual. Users should assess the applicability of the product and follow actual operating procedures. The final interpretation of this manual is reserved by our company.

Shenzhen Bat Wireless Technology Co,.Ltd

Office Add：Room 1301, 13th Floor, No. 8 Langhua Road, Xinshi Community, Dalang Street, Longhua District, Shenzhen

Email：marketing@batwireless.com

Tel：0755-21031236

BAT WIRELESS

Documentation

Version:	Aug-21-2025-A01
Date:	2025-08-21
Note:	First released
Author:	Carly / Lisa

Change Log